

Specifications:

Weight: 258g

Dimension: 168mm*158mm*105mm

Screen: 5 inch

Monitor: 16:9

Resolution: 800*600

Video format: NSTC/PAL (Automatic identification)

Receiver: 40 channels

Working voltage: 7V~15V (2S~4S)

Operating temperature: -20° ~ 80°

Power dissipation: 300mah

Included:

Goggles*1PCS

Head strap*1PCS

Eye ring*2PCS (Thick/Thin)

Power extension cord*1PCS

5.8G Antenna*1PCS

Velcro*2PCS

Function:

Shortcut Menu:

- 1: Button + and — adjusting Brightness directly (each press is 10% change)
- 2: Long press Menu button start to automatic search channel
- 3: Power display or current channel display: Single press arbitrarily button can showing current voltage and channel.

Menu:

- 1: Manual search, between 5.645~5.945(total 40 channels), press button+ or – to choose. Long press + or – for fast change.
- 2: Automatic search, very high speed to match the strongest 5.8G channel.
- 3: Brightness, press button+ or – to increase or reduce the brightness. Long press + or – for fast change.
- 4: Contrast, press button+ or – to increase or reduce. Long press + or – for fast change.
- 5: Color saturability, press button+ or – to increase or reduce. Long press + or – for fast change.

Jacks Function:插口功能:

- 1: External video input(4 pins), System will automatic get the input signal and exchange the working mode.
- 2: Video output(4 pins). Share the most primitive and authentic senses experience.
- 3: Audio output. (3 pins)

眼镜本体重量：258g
产品尺寸：168mm*158mm*105mm
显示屏：5 寸
画面比例：16:9
分辨率：800*600
画制格式：NSTC/PAL（自动识别）
接收机：40 频段
工作电压：7V~15V（2S~4S）
工作温度：-20° ~ 80°
功耗：300mah

产品清单：

眼镜本体*1PCS
头部挂带*1PCS
面部软垫*2PCS（厚/薄 各一）
电源延长线*1PCS
5.8G 天线*1PCS
束线扣*2PCS

眼镜功能菜单：

快捷菜单：

- 1：按键+ 和按键— 可以直接调整屏幕亮度，（调节幅度为 10% 一档）
- 2：长按菜单键可以直接进入快捷扫频模式。
- 3：电压显示或当前频点显示：短按任意键即可弹出电压显示和当前频点显示。

常规菜单：

- 1：手动选频，5.645~5.945（共 40 个频点）依次排列，通过按键+或—选择所需频点。长按按键+或—将进入快速变换模式。
- 2：自动扫频，超高速自动选择频点。
- 3：亮度调节，通过按键+或—选择所需亮度。长按按键+或—将进入快速变换模式。
- 4：对比度调节，通过按键+或—选择所需对比度。长按按键+或—将进入快速变换模式。
- 5：色彩调节，通过按键+或—选择所需色彩。长按按键+或—将进入快速变换模式。

插口功能：

- 1：外接视频输入（四段插头），系统将自动识别输入信号，切换工作模式。
- 2：视频输出（四段插头）。体验原画面分享。
- 3：音频输出。（三段插头）